



# Power generator

## FH 6541

Nr art. 28198

### Characteristic

- Voltage stabilization +5 -10 %
- Low level of THD  $\leq 4$  %
- Shortcut starting current 300 %
- Alternator insulation class H
- Alternator protection IP 54
- Full single phase power output socket 32 A 3P IP 67

### Technical parameters

<b>Frequency</b>	<b>50 Hz</b>
<b>Voltage</b>	<b>230 V</b>
<b>Maximum power</b>	<b>6,2 kW</b>
<b>Nominal power</b>	<b>5,6 kW</b>
<b>Prime current</b>	<b>24,3 A</b>
Engine	Honda
Model	GX 390
Capacity	389 cm <sup>3</sup>
Cooling	Powietrze
Cylinder	1
Stroke	4
Oil volume	1,1 L
Starting system	Manualny
Fuel	Benzyna
Fuel tank	6,1 L
Consumption (load 75%)	2,7 L / h
Noise level Lwa	97 dB(A)
Weight	97 kg
Length	745 mm
Width	530 mm
Height	495 mm

### Standard equipment

- Socket 230 V 16 A IP 67
- Socket 230 V 16 A 3P IP 67
- Socket 230 V 32 A 3P IP 67
- Overload protection
- Oil level sensor
- Hourmeter

### Optional and service equipment

- Exhaust hose Nr art. 15876
- Exhaust adapter Nr art. 10118
- Transportation set Nr art. 24480
- Service kit (air filter, spark plug, engine oil) Nr art. 16582

### Norms and Directives

- **2000/14/WE**  
Noise Directive 2005/88/WE
- **2006/42/WE**  
Machinery Directive
- **2014/35/WE**  
Low Voltage Directive
- **2014/30/WE**  
EC Directive