



# Power generator

## FH 3001

Nr art. 28151

### Characteristic

- Voltage stabilization  $\pm 5$  -10 %
- Low level of THD  $\leq 6$  %
- Shortcut starting current 300 %
- Alternator insulation class H
- Alternator protection IP IP 23

### Technical parameters

<b>Frequency</b>	<b>50 Hz</b>
<b>Voltage</b>	<b>230 V</b>
<b>Maximum power</b>	<b>3,0 kW</b>
<b>Nominal power</b>	<b>2,7 kW</b>
<b>Prime current</b>	<b>11,7 A</b>
Engine	Honda
Model	GX 200
Capacity	196 cm <sup>3</sup>
Cooling	Air
Cylinder	1
Stroke	4
Oil volume	0,6 L
Starting system	Manual
Fuel	Petrol
Fuel tank	3,1 L
Consumption (load 75%)	1,4 L / h
Noise level Lwa	96 dB(A)
Weight	37 kg
Length	580 mm
Width	395 mm
Height	405 mm

### Standard equipment

- 2 sockets 230 V 16 A
- Overload protection
- Oil level sensor

### Optional and service equipment

- Exhaust hose Nr art. 15876
- Exhaust adapter Nr art. 10117
- Hourmeter Nr art. 23300
- Service kit  
(air filter, spark plug, engine oil) Nr art. 16581

### Norms and Directives

- **2000/14/WE**  
Noise Directive 2005/88/WE
- **2006/42/WE**  
Machinery Directive
- **2014/35/WE**  
Low Voltage Directive
- **2014/30/WE**  
EC Directive