



Power generator

FH 9000 CRA

Nr art. 28682

Characteristic

- Digital voltage regulation $\pm 1,5\%$ on three phases
- Low level of THD $\leq 6\%$
- Shortcut starting current 300 %
- Alternator insulation class H
- Alternator protection IP IP 23
- Autonomy (at 75 % load) 18,5 h
- Low noise level Lwa 91 dB(A)
- Ready for manual and automatic operation

Technical parameters

Frequency	50 Hz
Voltage	400 / 230 V
Power 3~ max / nom.	8,5 kVA / 7,7 kVA (cos ϕ 0,8)
Prime current 3~	11,2 A
Power 1~ max / nom.	5,0 kW / 4,5 kW
Prime current 1~	19,6 A

Engine	Honda
Model	GX 390
Capacity	389 cm ³
Cooling	Air
Cylinder	1
Stroke	4
Oil volume	1,1 L
Starting system	Electric starter
Fuel	Petrol
Fuel tank	50 L
Consumption (load 75%)	2,7 L / h
Noise level Lwa	91 dB(A)

Weight	217 kg
Length	1100 mm
Width	600 mm
Height	830 mm

Standard equipment

- Digital AVR
- Socket 400 V 16 A
- 2 sockets 230 V 16 A
- Overload protection
- Oil level sensor
- Silencer with exhaust adapter
- Battery
- Connection for ATS panel
- Hourmeter

Optional and service equipment

- Exhaust hose Nr art. 15876
- Service kit (air filter, spark plug, engine oil) Nr art. 16582
- ATS panel Nr art. 30312
- Control panel housing Nr art. 28750

Norms and Directives

- **2000/14/WE**
Noise Directive 2005/88/WE
- **2006/42/WE**
Machinery Directive
- **2014/35/WE**
Low Voltage Directive
- **2014/30/WE**
EC Directive