



Power generator

F 4001 R

Nr art. 33565

Characteristic

- Voltage stabilization $\pm 1\%$
- Low level of THD $\leq 6\%$
- Shortcut starting current 300 %
- Alternator insulation class H
- Alternator protection IP 23

Technical parameters

Frequency	50 Hz
Voltage	230 V
Maximum power	4,0 kW
Nominal power	3,6 kW
Prime current	15,7 A
Engine	Rato
Model	R300
Capacity	301 cm ³
Cooling	Air
Cylinder	1
Stroke	4
Oil volume	1,1 L
Starting system	Manual
Fuel	Petrol
Fuel tank	5,4 L
Consumption (load 75%)	2,2 L / h
Noise level Lwa	96 dB(A)
Weight	53 kg
Length	650 mm
Width	520 mm
Height	490 mm

Standard equipment

- AVR
- 2 sockets 230 V 16 A
- Overload protection
- Oil level sensor

Optional and service equipment

- Hourmeter Nr art. 23300
- Transportation set Nr art. 24429
- Service kit
(air filter, spark plug, engine oil) Nr art. 16582

Norms and Directives

- **2000/14/WE**
Noise Directive 2005/88/WE
- **2006/42/WE**
Machinery Directive
- **2014/35/WE**
Low Voltage Directive
- **2014/30/WE**
EC Directive